



36CH Linux Network Video Recorder

NVR6536LR-PoE



- ▶ Support up to 36 channel H.265/H.264 IP camera
- ▶ Manage up to 16 channel PoE for IP cameras input
- ▶ Supports up to 8 Mega-pixel
- ▶ Power management for PoE channel
- ▶ Plug & play for easy installation
- ▶ Support e-SATA external storage
- ▶ Support RAID1/5 (optional)
- ▶ VGA& HDMI dual output, HDMI up to 4K2K
- ▶ Playback Smart search
- ▶ E-MAP
- ▶ Manual / schedule / event recording
- ▶ Free App (wecam_p2p) for monitoring via Android / iOS smart phone

Specification

System

| | |
|-------------------|--|
| Video Output | VGA x 1 up to 1080P HDMI x 1, up to 4K2K |
| USB Connector | USB 2.0 x 3 |
| Audio Input | 3.5mm jack to connect microphone |
| Audio Output | 3.5mm jack to connect amplified speaker |
| Record Storage | Internal Storage: SATA HDD x 8 External Storage: Local USB2.0x3, eSATA: x2 RAID: RAID 1/5 (Optional) |
| Power Supply | AC 100~240V |
| Power Output | RJ-45 x 16, PoE 802.3at |
| Power Consumption | HDDx8: 70W (No PoE output) No HDD: 26W (No PoE output) |
| Operating Temp. | 0~45°C / 32~113°F |
| Humidity | 0~80% RH (non-condensing) |
| GPIO | 4 Alarm in/ 1 Relay out |
| WAN Ethernet | RJ-45 x1, 10/100/1000 Mbps |
| Weight | 4KG |

Recording

| | |
|-----------------|---|
| Record Mode | Manual / Schedule / Event |
| Pre Recording | 5~60 sec |
| Playback search | Timeline search, Event list search, Smart search |

Remote Client Access

| | |
|-------------------|---|
| Client Software | Microsoft IE 11 or above Chrome Safari V5.1 or above Android => "wecam_p2p" iOS=> "wecam_p2p" |
| Connected Clients | Up to 10 clients simultaneously |

Video / Audio

| | |
|----------------------|---------------------------------------|
| Channel | Max.36 channels recording and display |
| IPCam Video input | 36 channels |
| Split screen display | 36CH (1, 4, 6, 9, 10, 13, 16, 25, 36) |
| Decompression | H.265, H.264 |
| IP Cam Resolution | Up to 4K2K |
| Throughput | (150Mbps) |